Three Phase Inverter For Europe

SE12.5K - SE20K



INVERTERS

Specifically designed to work with power optimizers

- Superior efficiency (98%)
- Quick and easy inverter commissioning directly from a smartphone using the SolarEdge SetApp
- Small, lightest in its class, and easy to install
- Built-in module-level monitoring
- Internet connection through Ethernet or Wireless

- IP65 Outdoor and indoor installation
- Fixed voltage inverter for longer strings
- Smart Energy Management control
- Advanced safety features integrated arc fault protection
- Optional RS485 surge protection



/ Three Phase Inverter

For Europe

SE12.5K - SE20K

Applicable to inverters with part number	SEXXK-XXXXXBXX4			SEXXK- XXXXIBXX4	
	SE12.5K	SE16K	SE17K	SE20K	
OUTPUT			_		
Rated AC Active Output Power	12500	16000	17000	20001*	,
Maximum AC Apparent Output Power	12500	16000	17000	20001*	١
AC Output Voltage - Line to Line / Line to Neutral (Nominal)	12300		/230	20001	١
AC Output Voltage - Line to Neutral (Range)	184 - 264.5				١
AC Frequency	50/60 ± 5				
AC Output Line Connections	20 23.2 24.6 29				,
Grids Supported - Three Phase	3 / N / PF (W YF With Neutral)			3 / N / PE (WYE with	
Utility Monitoring, Islanding Protection, Configurable Power Factor, Country Configurable Thresholds	Yes Neutral), 3 / PE				-
THD	≤3				
INPUT	1	_	-		
Maximum DC Power (Module STC)	16850	21600	22950	30000	
Transformer-less, Ungrounded	10050		'es	30000	\vdash
Maximum Input Voltage DC+ to DC-	1000				
Nominal Input Voltage DC+ to DC-	750				
Maximum Input Current	21	23.2	24.6	29	,
Reverse-Polarity Protection	21		es 24.0	23	-
Ground-Fault Isolation Detection		700kΩ Sensitivity ⁽¹⁾	C3	167kΩ Sensitivity ⁽¹⁾	H
Maximum Inverter Efficiency			98	107 KZ 2 SCH Sitivity	H
European Weighted Efficiency	97.7				H
Nighttime Power Consumption		< 2.5	1.1	< 4	
ADDITIONAL FEATURES		- 2.3		* * * * * * * * * * * * * * * * * * * *	_
Supported Communication Interfaces ⁽²⁾	R	S485 Ethernet Wi-Fi (ont	ional) ⁽³⁾ Cellular (ontiona	<u> </u>	П
Inverter Commissioning	RS485, Ethernet, Wi-Fi (optional) ⁽³⁾ Cellular (optional) With the SetApp mobile application using built-in Wi-Fi access point for local connection				\vdash
Smart Energy Management	Export Limitation				H
Arc Fault Protection	Integrated, User Configurable (According to UL1699B)				H
	Optional ⁽⁴⁾				H
RS485 Surge Protection	Optionar** Type II, field				H
DC Surge Protection		-		replaceable, integrated	
AC Surge Protection		=		Type II, field replaceable, optional	
STANDARD COMPLIANCE					
Safety	IEC-62103 (EN50178), IEC-62109, AS3100				Г
Grid Connection Standards ⁽⁵⁾	VDE-AR-N-4105, G99, AS-4777, EN50438, EN50549-1, CEI-021, VDE 0126-1-1, CEI-016, EN50549-1				
Emissions				IEC61000-6-2, IEC61000-6-3, IEC61000-3-11, IEC61000-3-12, Class A	
RoHS	Yes				
INSTALLATION SPECIFICATIONS					
AC Output Gland Diameter / Wire Cross Section	15-2	1mm / Solid wire 2.5-16 m	nm²	Cable diameter 19-28 mm / 4 - 16 mm ²	
DC Input		2 MC4 pairs		4 MC4 pairs	
Dimensions (H x W x D)		549 x 317 x 264		550 x 317 x 273	r
Weight	30.7 32			32	
Operating Temperature Range	-40 to +60 ⁽⁶⁾				
Cooling	Fan (user replaceable)				
Noise	< 50 < 62			(
Protection Rating	IP65 - outdoor and indoor				
Mounting	Brackets provided				

- (1) Where permitted by local regulation
- (2) Refer to Datasheets -> Communications category in Downloads page for specifications of optional communication options: https://www.solaredge.com/resource-library
- (3) Wi-Fi connectivity requires connection of an additional Wi-Fi component, ordered separately. For more details ask your SolarEdge sales person or refer to: https://www.solaredge.com/products/communication
- (4) An RS485 SPD plug-in can be purchased. Refer to: https://www.solaredge.com/sites/default/files/se_spd_plug_in_for_rs485_for_3ph_with_setapp_ds.pdf
- (5) For all standards refer to Certifications category in Downloads page: https://www.solaredge.com/resource-library
- (6) For power de-rating information refer to: https://www.solaredge.com/sites/default/files/se-temperature-derating-note.pdf
- (7) For SE15k and above, the minimum DC power should be 11KW

© SolarEdge Technologies, Ltd. All rights reserved. SOLAREDGE, the SolarEdge logo, OPTIMIZED BY SOLAREDGE are trademarks or registered trademarks of SolarEdge Technologies, Inc. All other trademarks mentioned herein are trademarks of their respective owners. Date: 07/2021 DS-000040-3.2-EU. Subject to change without notice.

